



52V Battery Charger

Charge RAMFAN 52V Lithium-Ion Battery packs from the fire apparatus or at the fire station. Place RAMFAN Battery charger at the station or in the apparatus compartment.

Features:

- **3 models:** AC or DC
- Communicates with battery packs to optimize cell voltage and monitor charge status to ensure full and safe charge
- **Onboard indicator light:**
Provides the status of the battery charge state

Batteries not included

Specifications

Part Numbers	M1C-6500AC	M1C-6500AC230	M1C-6500DC	EX150Li Integrated Charger
Power Source	115 VAC	230 VAC	12-24V DC	110/240 VAC
Output	52V			
Charge Current per battery	1.5A			AC Model: 1.5A DC Model: 0.8A
Dimensions (L/W/H)	14.1" x 10.5" x 2.6" / 358 x 266 x 66 mm			
Weight	10 lbs / 4.5 kg			