

**NOW, 2X  
FASTER  
CHARGING  
TIMES**



## 40V Battery Charger

Charge RAMFAN 40V Lithium-Ion Battery packs from the fire apparatus or at the fire station. Place RAMFAN Battery charger at the station or in the apparatus compartment.

### Features:

- **2 models:** AC or DC
- Communicates with battery packs to optimize cell voltage and monitor charge status to ensure full and safe charge
- **Charging Indicator Light**

Provides the status of the battery charge state



Batteries not included

### Specifications

| Part Numbers                         | R25515  | R25515DC  |
|--------------------------------------|---|-----------|
| Power Source                         | 115/230 VAC   | 12-24 VDC |
| Output                               | 42V   |           |
| Charge Time                          | 2 Hours   |           |
| Simultaneously Charges Two Batteries | 3A  |           |
| Dimensions (L/W/H)                   | 11-3/8" x 9-1/2" x 3-5/8" without Battery Packs<br>11-3/8" x 9-1/2" x 6-1/2" with Battery Pack(s) |           |
| Weight                               | 9 lbs / 4.08 kg   |           |

Mounting Template Available  
For more details see owners manual